

**SECTION 26 51 00
INTERIOR LIGHTING**

PART 1 - GENERAL

1.1 DESCRIPTION

This section specifies the furnishing, installation and connection of the interior lighting systems.

1.2 RELATED WORK

- A. Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS: General requirements that are common to more than one section of Division 26.
- B. Section 26 05 21, LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES (600 VOLTS AND BELOW): Cables and wiring.
- C. Section 26 27 26, WIRING DEVICES: Wiring devices used as part of the lighting systems.
- D. Section 26 05 26, GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS: Requirements for personnel safety and to provide a low impedance path to ground for possible ground fault currents.

1.3 QUALITY ASSURANCE

- A. Refer to Paragraph, QUALIFICATIONS, in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.
- B. Refer to Paragraph, GUARANTY, in Section 00 72 00, GENERAL CONDITIONS.

1.4 SUBMITTALS

- A. In accordance with Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS, submit the following:
- B. Shop Drawings:
 - 1. Sufficient information, clearly presented, shall be included to determine compliance with drawings and specifications.
 - 2. Include electrical ratings, dimensions, mounting details, materials, required clearances, terminations, wiring and connection diagrams, photometric data, ballasts, lenses, louvers, lamps, and controls.
 - 3. When catalog data and/or shop drawings for fluorescent fixtures are submitted for approval, photometric data from an independent testing laboratory shall be included with the submittal, indicating average brightness and efficiency of the fixture, as specified in specification or as shown on the drawings. Coefficient of utilization data will not be considered a suitable substitute.
- C. Manuals:
 - 1. Submit, simultaneously with the shop drawings companion copies of complete maintenance and operating manuals including technical data sheets, and information for ordering replacement parts.

2. Two weeks prior to the final inspection, submit four copies of the final updated maintenance and operating manuals, including any changes, to the Resident Engineer.

D. Certifications:

1. Two weeks prior to final inspection, submit four copies of the following certifications to the Resident Engineer:
 - a. Certification by the Contractor that the equipment has been properly installed, adjusted, and tested.
 - b. Include with shop drawings, certification from the manufacturers that all electronic high-frequency ballasts meet the transient protection required by IEEE C62.41, Cat. A. Include with initial shop drawing submittal.

1.5 APPLICABLE PUBLICATIONS

- A. Publications listed below (including amendments, addenda, revisions, supplements, and errata) form a part of this specification to the extent referenced. Publications are referenced in the text by designation only.
- B. American National Standards Institute (ANSI):
 - C78.1-91.....Fluorescent Lamps - Rapid-Start Types -
Dimensional and Electrical Characteristics
 - C78.2-91.....Fluorescent Lamps - Preheat-Start Types -
Dimensional and Electrical Characteristics
 - C78.3-91.....Fluorescent Lamps - Instart Start and Cold-
Cathode Types - Dimensional and Electrical
Characteristics
 - C78.376-91.....Chromaticity of Fluorescent Lamps (ANSI/NEMA
C78/376-96)
- C. Certified Ballast Manufacturers Association (CBM):
Requirements for Ballast Certification.
- D. Institute of Electrical and Electronic Engineers (IEEE):
 - C62.41-91.....Recommended Practice on Surge Voltage in Low
Voltage AC Power Circuits
- E. National Fire Protection Association (NFPA):
 - 70-02.....National Electrical Code (NEC)
 - 101-00.....Life Safety Code
- F. National Electrical Manufacturer's Association (NEMA)
 - C82.1-97.....Ballasts for Fluorescent Lamps - Specifications
 - C82.2-02.....Method of Measurement of Fluorescent Lamp
Ballasts
 - C82.4-02.....Ballasts for High-Intensity-Discharge and Low-
Pressure Sodium Lamps
 - C82.11-02.....High Frequency Fluorescent Lamp Ballasts

G. Underwriters Laboratories, Inc. (UL):

496-96.....Edison-Base Lampholders

542-99.....Lampholders, Starters, and Starter Holders for
Fluorescent Lamps844-95.....Electric Lighting Fixtures for Use in Hazardous
(Classified) Locations

924-95.....Emergency Lighting and Power Equipment

935-01.....Fluorescent-Lamp Ballasts

1029-94.....High-Intensity-Discharge Lamp Ballasts

1598-00.....Luminaires

H. Federal Communications Commission (FCC):

Code of Federal Regulations (CFR), Title 47, Part 18

PART 2 - PRODUCTS**2.1 LIGHTING FIXTURES (LUMINAIRES)**

A. Shall be in accordance with NFPA 70, UL 1598 and shall be as shown on drawings and as specified.

B. Sheet Metal:

1. Shall be formed to prevent warping and sagging. Housing, trim and lens frame shall be true, straight (unless intentionally curved) and parallel to each other as designed.
2. Wireways and fittings shall be free of burrs and sharp edges and shall accommodate internal and branch circuit wiring without damage to the wiring.
3. Where lighting fixtures are detailed with minimum 20 gauge housing, minimum 22 gauge housings will be acceptable provided they have strengthening embossed rib and break formations, which give the equivalent rigidity of a 20 gauge housing.
4. When installed, any exposed fixture housing surface, trim frame, door frame and lens frame shall be free of light leaks; lens doors shall close in a light tight manner.
5. Hinged door closure frames shall operate smoothly without binding when the fixture is in the installed position, and latches shall function easily by finger action without the use of tools.

C. Ballasts shall be serviceable while the fixture is in its normally installed position, and shall not be mounted to removable reflectors or wireway covers unless so specified.

D. Lamp Sockets:

1. Fluorescent: Lampholder contacts shall be the biting edge type or phosphorous-bronze with silver flash contact surface type and shall conform to the applicable requirements of UL 542. Contacts for recessed double contact lampholders and for slimline lampholders

- shall be silver plated. Lampholders for bi-pin lamps, with the exception of those for "U" type lamps, shall be of the telescoping compression type, or of the single slot entry type requiring a one-quarter turn of the lamp after insertion.
2. Incandescent: Shall have porcelain enclosures and conform to the applicable requirements of UL 496.
 3. High Intensity Discharge (H.I.D.): Shall have porcelain enclosures.
- E. Recessed incandescent fixtures mounted in an insulated ceiling shall be listed for use in insulated ceilings.
- F. Fluorescent fixtures with louvers or light transmitting panels shall have hinges, latches and safety catches to facilitate safe, convenient cleaning and relamping. Vapor tight fixtures shall have pressure clamping devices in lieu of the latches.
- G. Mechanical Safety: Lighting fixture closures (lens doors, trim frame, hinged housings, etc.) shall be retained in a secure manner by captive screws, chains, captive hinges or fasteners such that they cannot be accidentally dislodged during normal operation or routine maintenance.
- H. Metal Finishes:
1. The manufacturer shall apply his standard finish (unless otherwise specified) over a corrosion resistant primer, after cleaning to free the metal surfaces of rust, grease, dirt and other deposits. Edges of pre-finished sheet metal exposed during forming, stamping or shearing processes shall be finished in a similar corrosion resistant manner to match the adjacent surface(s). Fixture finish shall be free of stains or evidence of rusting, blistering, or flaking.
 2. Interior light reflecting finishes shall be white with not less than 85 percent reflectances, except where otherwise shown on the drawing.
 3. Exterior finishes shall be as shown on the drawings.
- I. Provide all lighting fixtures with a specific means for grounding their metallic wireways and housings to an equipment grounding conductor.
- J. Light Transmitting Components for Fluorescent Fixtures:
1. Shall be 100 percent virgin acrylic plastic or water white, annealed, crystal glass.
 2. Flat lens panels shall have not less than 3.2 mm (1/8 inch) of average thickness. The average thickness shall be determined by adding the maximum thickness to the minimum unpenetrated thickness and dividing the sum by 2.
 3. Unless otherwise specified, lenses, diffusers and louvers shall be retained firmly in a metal frame by clips or clamping ring in such a manner as to allow expansion and contraction of the lens without distortion or cracking.

- K. Lighting Fixtures in Hazardous Areas: Fixtures shall be suitable for installation in flammable atmospheres (Class and Group) as defined in NFPA 70 and shall comply with UL 844.
- L. Compact fluorescent fixtures shall be manufactured specifically for compact fluorescent lamps with ballasts integral to the fixture. Assemblies designed to retrofit incandescent fixtures are prohibited except when specifically indicated for renovation of existing fixtures. Fixtures shall be designed for lamps as specified.

2.2 FLUORESCENT LAMP BALLASTS

- A. Where applicable, fluorescent lamps and ballasts shall comply with the National Energy Policy Act of 1992.
- B. Ballasts shall comply with NEMA 82.1, 82.2 and 82.11, NFPA 70, and UL 935 unless otherwise specified.
- C. Lamp types F32T8 and F32T8/U shall be operated by electronic, high frequency ballasts. All other fluorescent lamp types shall be operated by the standard energy saving electromagnetic core-and-coil ballasts. For these applications, the lamps shall be operated by core-and-coil ballasts where specifically required on the drawings as "core-and-coil".
- D. Electronic high-frequency ballasts:
 - 1. Ballasts shall operate the lamps at a frequency between 20 and 60 KHz from an input frequency of 60Hz.
 - 2. Ballast package:
 - a. Size: The ballast case shall be sized to be physically interchangeable with standard core-and-coil ballasts and suitable for standard mounting in new or existing lighting fixtures.
 - b. Case marking: Mark the ballast to indicate the required supply voltage, frequency, RMS current, current surge during starting, input watts, and power factor at the design center voltage, open circuit voltage, crest factor and efficacy.
 - 3. Performance:
 - a. Light output:
 - 1) At the design voltage, the light output shall be at least equal to that obtained by a core-and-coil ballasted system meeting ANSI, NEMA and CBM standards. The comparison test shall be measured in the same fixture at 25 degrees C (plus or minus one degree) ambient room temperature.
 - 2) Tests shall be made in fixtures designed only for the number of lamps being tested.
 - 3) For other applications (higher ambients, etc.) the tests should be operated with equivalent lamp wall temperatures plus or minus 4 degrees C.

- b. Efficacy: The efficacy of the high-frequency, electronically ballasted system shall be at least 15 percent greater than the equivalent CBM core-and-coil ballasted system (see "Light output" above).
- c. Starting: The ballast shall be capable of starting and maintaining operation of lamps at an ambient temperature of 10 degrees C (50 degree F) or more for an input voltage of plus or minus 10 percent about the center design voltage unless otherwise indicated. The ballast shall never be started in the instant start mode at any temperature.
- d. Operation:
 - 1) The ballast shall safely and reliably operate in a room ambient temperature from 10 degrees C (50 degree F) to 40 degrees C (105 degree F).
 - 2) The light output shall not vary by more than plus or minus 5 percent for a plus or minus 10 percent variation of the input voltage about the center design voltage. Light output shall remain constant for a plus or minus 5 percent variation of the input voltage.
 - 3) The ballast shall operate the lamps in a manner that will not adversely curtail the normal life of the lamp.
- e. Transient protection: The ballast shall comply with IEEE C62.41, Cat. A.
- f. Flicker: The flicker shall be less than 5 percent and without visible flicker.
- g. Noise: The audible noise levels should be equivalent to or better than the Class A rating of CBM certified ballasts.
- h. Electromagnetic Interference (EMI) and Radio Frequency Interference (RFI): The EMI and RFI limits shall meet the requirements of the Federal Communications Commission Rules and Regulations (CFR 47 Part 18).
- i. Rated life: The ballast shall have a rated life of 10 years or 30,000 hours (based on a 10 hour day).
- j. The two-lamp ballast shall safely operate two F32T8 RS, 32- watt lamps or two F32T8/U lamps. The single lamp ballast shall safely operate one F32T8 RS, 32-watt lamp or one F32T8/U lamp.
- k. Power factor: Not less than 95 percent.
- l. Reliability:
 - 1) Labels: Ballasts must be labeled or listed by UL and CBM/ETL.
 - 2) Submit, simultaneously with shop drawings, a certified test report by an independent testing laboratory showing that the

electronic ballasts meet or exceed all the performance requirements in this specification.

- m. Total harmonic distortion (THD) shall be less than 10 percent.
- E. Core-and-coil ballasts (for lamps other than F32T8 and F32T8/U or where shown on drawings as "core-and-coil"):
 - 1. Shall be rapid starting type.
 - 2. Shall comply with NEMA 82.1 and UL 935.
 - 3. Shall be UL Class P with automatic-resetting, internal, thermal protection.
 - 4. Shall be CBM/ETL certified.
 - 5. Power factor shall be not less than 95 percent. Capacitors in ballasts shall not contain PCB (Polychlorinated Biphenyl) fluids or other fluids recognized as hazardous when discharged into the environment.
 - 6. Sound ratings shall be Class A or better, except for ballast sizes which are not available with Class A ratings, as standard products from any manufacturer. Ballasts which are not available with Class A ratings shall have the quietest ratings available.
 - 7. Where core-and-coil ballasts are specified or detailed in lieu of the normally required electronic high-frequency types, two lamp ballasts shall be energy-saving type, UL listed to operate F40T12 rapid start lamps for both standard 40 watt lamps and the reduced wattage 35/34 watts energy-saving lamps. Lamp output shall be within 5 percent of nominal rating. When operating energy-saving lamps, the input watts to the ballast shall not exceed 78 watts at 120 V.A.C. or 79 watts at 277 V.A.C. Energy-saving type ballasts should not be used in ambient temperatures below manufacturer's recommendations.
- F. Ballasts for lighting fixtures controlled by dimming devices shall be the electronic, high frequency type as specified herein, equipped for dimming and conform to the recommendations of the manufacturer of the associated dimming devices to assure satisfactory operation of the lighting system.
- G. All ballasts serving straight or "U" type lamps shall be mounted by four non-turning studs (or captive bolts) equipped with lock washers and nuts or locking type nuts, or by four thread cutting (TC) sheet metal screws which are firmly secured against the fixture body (or wireway) to maximize dissipation of heat and minimize noise. Exception: electronic high-frequency ballasts may be mounted at a minimum of two points, one at each end of unit.

- H. Ballasts shall be serviceable while the fixture is in its normally installed position, and shall not be mounted to removable reflectors or wireway covers unless so specified.
- I. To facilitate multi-level lamp switching, lamps within fixture shall be wired with the outermost lamp at both sides of the fixture on the same ballast, the next inward pair on another ballast and so on to the innermost lamp (or pair of lamps). Within a given room, each switch shall uniformly control the same corresponding lamp (or lamp pairs) in all fixture units that are being controlled.
- J. Where three-lamp fixtures are indicated, unless switching arrangements dictate otherwise, utilize a common two-lamp ballast to operate the center lamp in pairs of adjacent units that are mounted in a continuous row. The ballast fixture and slave-lamp fixture shall be factory wired with leads or plug devices to facilitate this circuiting. Individually mounted fixtures and the odd fixture in a row shall utilize a single-lamp ballast for operation of the center lamp.

2.3 EXIT LIGHT FIXTURES

- A. Exit light fixtures shall meet applicable requirements of NFPA 101 and UL 924.
- B. Housing and Canopy:
 - 1. Shall be made of cast or extruded aluminum, or rolled steel.
 - 2. Optional steel housing shall be a minimum 20 gauge thick or equivalent strength aluminum.
 - 3. Steel housing shall have baked enamel over corrosion resistant, matte black or ivory white primer.
- C. Door frame shall be cast or extruded aluminum, and hinged with latch.
- D. Finish shall be satin or fine-grain brushed aluminum.
- E. There shall be no radioactive material used in the fixtures.
- F. Fixtures:
 - 1. Inscription panels shall be cast or stamped aluminum a minimum of 2.25 mm (0.090 inch) thick, stenciled with 150 mm (6 inch) high letters, baked with red color stable plastic or fiberglass. Lamps shall be luminous red Light Emitting Diodes (LED) mounted in center of letters on red color stable plastic or fiberglass. The LED shall be rated minimum 25 years life; maximum of 3.5 watts for single face and 7 watts for double-faced fixtures that do not use diffuser panels in front of the LEDs. LED exit light fixtures that use diffuser panels shall require a maximum of 1.0 watt per fixture for single or double face fixtures.
 - 2. Double-Faced Fixtures: Provide double-faced fixtures where required or as shown on drawings.

3. Directional Arrows: Provide directional arrows as part of the inscription panel where required or as shown on drawings. Directional arrows shall be the "chevron-type" of similar size and width as the letters and meet the requirements of NFPA 101.

G. Voltages: Fixtures shall be wired for 277-volt operation.

PART 3 - EXECUTION

3.1 INSTALLATION

- A. Installation shall be in accordance with the NEC, manufacturer's instructions and as shown on the drawings or specified.
- B. Align, mount and level the lighting fixtures uniformly.
- C. Avoid interference with and provide clearance for equipment. Where the indicated locations for the lighting fixtures conflict with the locations for equipment, change the locations for the lighting fixtures by the minimum distances necessary as approved by the Resident Engineer.
- D. For suspended lighting fixtures, the mounting heights shall provide the clearances between the bottoms of the fixtures and the finished floors as shown on the drawings.
- E. Fluorescent bed light fixtures shall be attached to the studs in the walls. Attachment to gypsum board only is not acceptable.
- F. Lighting Fixture Supports:
 1. Shall provide support for all of the fixtures. Supports may be anchored to channels of the ceiling construction, to the structural slab or to structural members within a partition, or above a suspended ceiling.
 2. Shall maintain the fixture positions after cleaning and relamping.
 3. Shall support the lighting fixtures without causing the ceiling or partition to deflect.

- - - E N D - - -