

## **SECTION 26 29 11 MOTOR CONTROLLERS**

### **PART 1 - GENERAL**

#### **1.1 DESCRIPTION**

- A. This section specifies the furnishing, installation, connection, and testing of motor controllers, including all low- and medium-voltage motor controllers and manual motor controllers, indicated as motor controllers in this section, and low-voltage variable speed motor controllers.
- B. Motor controllers, whether furnished with the equipment specified in other sections or otherwise (with the exception of elevator motor controllers specified in Division 14 and fire pump controllers specified in Division 21), shall meet this specification and all related specifications.

#### **1.2 RELATED WORK**

- A. Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS: Requirements that apply to all sections of Division 26.

#### **1.3 QUALITY ASSURANCE**

- A. Refer to Paragraph, QUALIFICATIONS (PRODUCTS AND SERVICES), in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.

#### **1.4 SUBMITTALS**

- A. Submit six copies of the following in accordance with Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.
  - 1. Shop Drawings:
    - a. Submit sufficient information to demonstrate compliance with drawings and specifications.
    - b. Include electrical ratings, dimensions, weights, mounting details, materials, overcurrent protection devices, overload relays, sizes of enclosures, wiring diagrams, starting characteristics, interlocking, and accessories.
  - 2. Manuals:
    - a. Submit, simultaneously with the shop drawings, companion copies of complete maintenance and operating manuals, including technical data sheets, wiring diagrams, and information for ordering replacement parts.
      - 1) Wiring diagrams shall have their terminals identified to facilitate installation, maintenance, and operation.
      - 2) Wiring diagrams shall indicate internal wiring for each item of equipment and interconnections between the items of equipment.
      - 3) Elementary schematic diagrams shall be provided for clarity of operation.

- 4) Include the catalog numbers for the correct sizes of overload relays for the motor controllers.
- b. If changes have been made to the maintenance and operating manuals originally submitted, submit updated maintenance and operating manuals two weeks prior to the final inspection.
3. Certifications: Two weeks prior to final inspection, submit the following.
  - a. Certification by the manufacturer that the motor controllers conform to the requirements of the drawings and specifications.
  - b. Certification by the Contractor that the motor controllers have been properly installed, adjusted, and tested.

## 1.5 APPLICABLE PUBLICATIONS

- A. Publications listed below (including amendments, addenda, revisions, supplements, and errata) form a part of this specification to the extent referenced. Publications are referenced in the text by basic designation only.
- B. National Electrical Manufacturers Association (NEMA):
  - ICS 1-08 ..... Industrial Control and Systems: General Requirements
  - ICS 1.1-09..... Safety Guidelines for the Application, Installation and Maintenance of Solid State Control
  - ICS 2-05 ..... Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 Volts
  - ICS 4-05 ..... Industrial Control and Systems: Terminal Blocks
- C. National Fire Protection Association (NFPA):
  - 70-14 ..... National Electrical Code (NEC)
- D. Underwriters Laboratories Inc. (UL):
  - 508A-07 ..... Industrial Control Panels
  - 508C-07 ..... Power Conversion Equipment

## PART 2 - PRODUCTS

### 2.1 MOTOR CONTROLLERS

- A. Motor controllers shall comply with IEEE, NEMA, NFPA, UL, and as shown on the drawings.
- B. Motor controllers shall be separately enclosed, unless part of another assembly. For installation in motor control centers, provide plug-in, draw-out type motor controllers up through NEMA size 4. NEMA size 5 and above require bolted connections.
- C. Motor controllers shall be combination type, with magnetic controller per Paragraph 2.3 below and with motor circuit protector disconnecting means, with external operating handle with lock-open padlocking positions and ON-OFF position indicator.
  1. Motor Circuit Protectors:
    - a. Magnetic trip only.

- b. Bolt-on type with a minimum interrupting rating as indicated on the drawings.
  - c. Equipped with automatic, adjustable magnetic trip. Magnetic trip shall be adjustable up to 1300% of the motor full load amperes.
- D. Motor control circuits:
  - 1. Shall operate at not more than 120 Volts.
  - 2. Shall be grounded, except where the equipment manufacturer recommends that the control circuits be isolated.
  - 3. For each motor operating over 120 Volts, incorporate a separate, heavy duty, control transformer within each motor controller enclosure.
  - 4. Incorporate primary and secondary overcurrent protection for the control power transformers.
- E. Overload relays:
  - 1. Thermal type. Devices shall be NEMA type.
  - 2. One for each pole.
  - 3. External overload relay reset pushbutton on the door of each motor controller enclosure.
  - 4. Overload relays shall be matched to nameplate full-load current of actual protected motor and with appropriate adjustment for duty cycle.
  - 5. Thermal overload relays shall be tamperproof, not affected by vibration, manual reset, sensitive to single-phasing, and shall have selectable trip classes of 10, 20 and 30.
- F. Hand-Off-Automatic (H-O-A) switch is required unless specifically stated on the drawings as not required for a particular controller. H-O-A switch shall be operable without opening enclosure door. H-O-A switch is not required for manual motor controllers.
- G. Incorporate into each control circuit a 120 Volt, electronic time-delay relay (ON delay), minimum adjustable range from 0.3 to 10 minutes, with transient protection. Time-delay relay is not required where H-O-A switch is not required.
- H. Unless noted otherwise, equip each motor controller with not less than two normally open (N.O.) and two normally closed (N.C.) auxiliary contacts.
- I. Provide green (RUN) and red (STOP) pilot lights.
- J. Motor controllers incorporated within equipment assemblies shall also be designed for the specific requirements of the assemblies.
- K. Additional requirements for specific motor controllers, as indicated in other specification sections, shall also apply.

## **2.2 MAGNETIC MOTOR CONTROLLERS**

- A. Shall be in accordance with applicable requirements of 2.1 above.
- B. Controllers shall be general-purpose, Class A magnetic controllers for induction motors rated in horsepower. Minimum NEMA size 0.

- C. Where combination motor controllers are used, combine controller with protective or disconnect device in a common enclosure.
- D. Provide phase loss protection for each controller, with contacts to de-energize the controller upon loss of any phase.
- E. Unless otherwise indicated, provide full voltage non-reversing across-the-line mechanisms for motors less than 75 HP, closed by coil action and opened by gravity. For motors 75 HP and larger, provide reduced-voltage or variable speed controllers as shown on the drawings. Equip controllers with 120 VAC coils and individual control transformer unless otherwise noted.

## **PART 3 - EXECUTION**

### **3.1 INSTALLATION**

- A. Install motor controllers in accordance with the NEC, as shown on the drawings, and as recommended by the manufacturer.
- B. In seismic areas, motor controllers shall be adequately anchored and braced per details on structural contract drawings to withstand the seismic forces at the location where installed.
- C. Adjust trip settings of circuit breakers and motor circuit protectors with adjustable instantaneous trip elements. Initially adjust at six times the motor nameplate full-load ampere ratings and attempt to start motors several times, allowing for motor cooldown between starts. If tripping occurs on motor inrush, adjust settings in increments until motors start without tripping. Do not exceed eight times the motor full-load amperes (or 11 times for NEMA Premium Efficiency motors if required). Where these maximum settings do not allow starting of a motor, notify COR before increasing settings.

### **3.2 ACCEPTANCE CHECKS AND TESTS**

- A. Perform manufacturer's required field tests in accordance with the manufacturer's recommendations. In addition, include the following:
  - 1. Visual Inspection and Tests:
    - a. Compare equipment nameplate data with specifications and approved shop drawings.
    - b. Inspect physical, electrical, and mechanical condition.
    - c. Verify appropriate anchorage, required area clearances, and correct alignment.
    - d. Verify that circuit breaker, motor circuit protector, and fuse sizes and types correspond to approved shop drawings.
    - e. Verify overload relay ratings are correct.
    - f. Vacuum-clean enclosure interior. Clean enclosure exterior.
    - g. Verify tightness of accessible bolted electrical connections by calibrated torque-wrench method in accordance with manufacturer's published data.
    - h. Test all control and safety features of the motor controllers.

### **3.3 FOLLOW-UP VERIFICATION**

- A. Upon completion of acceptance checks, settings, and tests, the Contractor shall show by demonstration in service that the motor controllers are in good operating condition and properly performing the intended functions.

### **3.4 SPARE PARTS**

- A. Two weeks prior to the final inspection, provide one complete set of spare fuses for each motor controller.

### **3.5 INSTRUCTION**

- A. Furnish the services of a factory-trained technician for two 4-hour training periods for instructing personnel in the maintenance and operation of the motor controllers, on the dates requested by the COR.

**END OF SECTION 26 29 11**