

SECTION 26 51 00
INTERIOR LIGHTING

PART 1 - GENERAL

1.1 DESCRIPTION

This section specifies the furnishing, installation and connection of the interior lighting systems.

1.2 RELATED WORK

- A. Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS: General requirements that are common to more than one section of Division 26.
- B. Section 26 05 21, LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES (600 VOLTS AND BELOW): Cables and wiring.
- C. Section 26 27 26, WIRING DEVICES: Wiring devices used as part of the lighting systems.
- D. Section 26 05 26, GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS: Requirements for personnel safety and to provide a low impedance path to ground for possible ground fault currents.

1.3 QUALITY ASSURANCE

- A. Refer to Paragraph, QUALIFICATIONS, in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.
- B. Refer to Paragraph, GUARANTY, in the, GENERAL CONDITIONS.

1.4 SUBMITTALS

- A. In accordance with Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS, submit the following:
- B. Shop Drawings:
 - 1. Sufficient information, clearly presented, shall be included to determine compliance with drawings and specifications.
 - 2. Include electrical ratings, dimensions, mounting details, materials, required clearances, terminations, wiring and connection diagrams, photometric data, ballasts, lenses, louvers, lamps, and controls.
 - 3. When catalog data and/or shop drawings for fluorescent fixtures are submitted for approval, photometric data from an independent testing laboratory shall be included with the submittal, indicating average brightness and efficiency of the fixture, as specified in specification or as shown on the drawings. Coefficient of utilization data will not be considered a suitable substitute.
- C. Samples:
 - 1. Simultaneously with the shop drawing and catalog cut submittal, deliver to the COR a sample of each lighting fixture types: A, B, & C for approval. The approved samples shall be installed in the location

**SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4**

- 101-00.....Life Safety Code
- F. National Electrical Manufacturer's Association (NEMA)
 - C82.1-97.....Ballasts for Fluorescent Lamps - Specifications
 - C82.2-02.....Method of Measurement of Fluorescent Lamp
Ballasts
 - C82.4-02.....Ballasts for High-Intensity-Discharge and Low-
Pressure Sodium Lamps
 - C82.11-02.....High Frequency Fluorescent Lamp Ballasts
- G. Underwriters Laboratories, Inc. (UL):
 - 496-96.....Edison-Base Lampholders
 - 542-99.....Lampholders, Starters, and Starter Holders for
Fluorescent Lamps
 - 844-95.....Electric Lighting Fixtures for Use in Hazardous
(Classified) Locations
 - 924-95.....Emergency Lighting and Power Equipment
 - 935-01.....Fluorescent-Lamp Ballasts
 - 1029-94.....High-Intensity-Discharge Lamp Ballasts
 - 1598-00.....Luminaires
- H. Federal Communications Commission (FCC):
 - Code of Federal Regulations (CFR), Title 47, Part 18

PART 2 - PRODUCTS

2.1 LIGHTING FIXTURES (LUMINAIRES)

- A. Shall be in accordance with NFPA 70, UL 1598 and shall be as shown on drawings and as specified.
- B. Sheet Metal:
 - 1. Shall be formed to prevent warping and sagging. Housing, trim and lens frame shall be true, straight (unless intentionally curved) and parallel to each other as designed.
 - 2. Wireways and fittings shall be free of burrs and sharp edges and shall accommodate internal and branch circuit wiring without damage to the wiring.
 - 3. Where lighting fixtures are detailed with minimum 20 gauge housing, minimum 22 gauge housings will be acceptable provided they have strengthening embossed rib and break formations, which give the equivalent rigidity of a 20 gauge housing.
 - 4. When installed, any exposed fixture housing surface, trim frame, door frame and lens frame shall be free of light leaks; lens doors shall close in a light tight manner.

SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4

5. Hinged door closure frames shall operate smoothly without binding when the fixture is in the installed position, and latches shall function easily by finger action without the use of tools.
- C. Ballasts shall be serviceable while the fixture is in its normally installed position, and shall not be mounted to removable reflectors or wireway covers unless so specified.
- D. Lamp Sockets:
1. Fluorescent: Lampholder contacts shall be the biting edge type or phosphorous-bronze with silver flash contact surface type and shall conform to the applicable requirements of UL 542. Contacts for recessed double contact lampholders and for slimline lampholders shall be silver plated. Lampholders for bi-pin lamps, with the exception of those for "U" type lamps, shall be of the telescoping compression type, or of the single slot entry type requiring a one-quarter turn of the lamp after insertion.
- E. Fluorescent fixtures with louvers or light transmitting panels shall have hinges, latches and safety catches to facilitate safe, convenient cleaning and relamping. Vapor tight fixtures shall have pressure clamping devices in lieu of the latches.
- F. Mechanical Safety: Lighting fixture closures (lens doors, trim frame, hinged housings, etc.) shall be retained in a secure manner by captive screws, chains, captive hinges or fasteners such that they cannot be accidentally dislodged during normal operation or routine maintenance.
- G. Metal Finishes:
1. The manufacturer shall apply his standard finish (unless otherwise specified) over a corrosion resistant primer, after cleaning to free the metal surfaces of rust, grease, dirt and other deposits. Edges of pre-finished sheet metal exposed during forming, stamping or shearing processes shall be finished in a similar corrosion resistant manner to match the adjacent surface(s). Fixture finish shall be free of stains or evidence of rusting, blistering, or flaking.
 2. Interior light reflecting finishes shall be white with not less than 85 percent reflectances, except where otherwise shown on the drawing.
 3. Exterior finishes shall be as shown on the drawings.
- H. Provide all lighting fixtures with a specific means for grounding their metallic wireways and housings to an equipment grounding conductor.
- I. Light Transmitting Components for Fluorescent Fixtures:
1. Shall be 100 percent virgin acrylic plastic or water white, annealed, crystal glass.

2. Flat lens panels shall have not less than 3.2 mm (1/8 inch) of average thickness. The average thickness shall be determined by adding the maximum thickness to the minimum unpenetrated thickness and dividing the sum by 2.
3. Unless otherwise specified, lenses, diffusers and louvers shall be retained firmly in a metal frame by clips or clamping ring in such a manner as to allow expansion and contraction of the lens without distortion or cracking.

J. Lighting Fixtures in Hazardous Areas: Fixtures shall be suitable for installation in flammable atmospheres (Class and Group) as defined in NFPA 70 and shall comply with UL 844.

2.2 FLUORESCENT LAMP BALLASTS

- A. Where applicable, fluorescent lamps and ballasts shall comply with the National Energy Policy Act of 1992.
- B. Ballasts shall comply with NEMA 82.1, 82.2 and 82.11, NFPA 70, and UL 935 unless otherwise specified.
- C. Lamp types F32T8 and F32T8/U shall be operated by electronic, high frequency ballasts. All other fluorescent lamp types shall be operated by the standard energy saving electromagnetic core-and-coil ballasts. For these applications, the lamps shall be operated by core-and-coil ballasts where specifically required on the drawings as "core-and-coil".
- D. Electronic high-frequency ballasts:
 1. Ballasts shall operate the lamps at a frequency between 20 and 60 KHz from an input frequency of 60Hz.
 2. Ballast package:
 - a. Size: The ballast case shall be sized to be physically interchangeable with standard core-and-coil ballasts and suitable for standard mounting in new or existing lighting fixtures.
 - b. Case marking: Mark the ballast to indicate the required supply voltage, frequency, RMS current, current surge during starting, input watts, and power factor at the design center voltage, open circuit voltage, crest factor and efficacy.
 3. Performance:
 - a. Light output:
 - 1) At the design voltage, the light output shall be at least equal to that obtained by a core-and-coil ballasted system meeting ANSI, NEMA and CBM standards. The comparison test shall be measured in the same fixture at 25 degrees C (plus or minus one degree) ambient room temperature.

**SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4**

- 2) Tests shall be made in fixtures designed only for the number of lamps being tested.
 - 3) For other applications (higher ambients, etc.) the tests should be operated with equivalent lamp wall temperatures plus or minus 4 degrees C.
- b. Efficacy: The efficacy of the high-frequency, electronically ballasted system shall be at least 15 percent greater than the equivalent CBM core-and-coil ballasted system (see "Light output" above).
- c. Starting: The ballast shall be capable of starting and maintaining operation of lamps at an ambient temperature of 10 degrees C (50 degree F) or more for an input voltage of plus or minus 10 percent about the center design voltage unless otherwise indicated. The ballast shall never be started in the instant start mode at any temperature.
- d. Operation:
- 1) The ballast shall safely and reliably operate in a room ambient temperature from 10 degrees C (50 degree F) to 40 degrees C (105 degree F).
 - 2) The light output shall not vary by more than plus or minus 5 percent for a plus or minus 10 percent variation of the input voltage about the center design voltage. Light output shall remain constant for a plus or minus 5 percent variation of the input voltage.
 - 3) The ballast shall operate the lamps in a manner that will not adversely curtail the normal life of the lamp.
- e. Transient protection: The ballast shall comply with IEEE C62.41, Cat. A.
- f. Flicker: The flicker shall be less than 5 percent and without visible flicker.
- g. Noise: The audible noise levels should be equivalent to or better than the Class A rating of CBM certified ballasts.
- h. Electromagnetic Interference (EMI) and Radio Frequency Interference (RFI): The EMI and RFI limits shall meet the requirements of the Federal Communications Commission Rules and Regulations (CFR 47 Part 18).
- i. Rated life: The ballast shall have a rated life of 10 years or 30,000 hours (based on a 10 hour day).

SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4

- j. The two-lamp ballast shall safely operate two F32T8 RS, 32- watt lamps or two F32T8/U lamps. The single lamp ballast shall safely operate one F32T8 RS, 32-watt lamp or one F32T8/U lamp.
 - k. Power factor: Not less than 95 percent.
 - l. Reliability:
 - 1) Labels: Ballasts must be labeled or listed by UL and CBM/ETL.
 - 2) Submit, simultaneously with shop drawings, a certified test report by an independent testing laboratory showing that the electronic ballasts meet or exceed all the performance requirements in this specification.
 - m. Total harmonic distortion (THD) shall be less than 10 percent.
- E. Core-and-coil ballasts (for lamps other than F32T8 and F32T8/U or where shown on drawings as "core-and-coil"):
- 1. Shall be rapid starting type.
 - 2. Shall comply with NEMA 82.1 and UL 935.
 - 3. Shall be UL Class P with automatic-resetting, internal, thermal protection.
 - 4. Shall be CBM/ETL certified.
 - 5. Power factor shall be not less than 95 percent. Capacitors in ballasts shall not contain PCB (Polychlorinated Biphenyl) fluids or other fluids recognized as hazardous when discharged into the environment.
 - 6. Sound ratings shall be Class A or better, except for ballast sizes which are not available with Class A ratings, as standard products from any manufacturer. Ballasts which are not available with Class A ratings shall have the quietest ratings available.
 - 7. Where core-and-coil ballasts are specified or detailed in lieu of the normally required electronic high-frequency types, two lamp ballasts shall be energy-saving type, UL listed to operate F40T12 rapid start lamps for both standard 40 watt lamps and the reduced wattage 35/34 watts energy-saving lamps. Lamp output shall be within 5 percent of nominal rating. When operating energy-saving lamps, the input watts to the ballast shall not exceed 78 watts at 120 V.A.C. or 79 watts at 277 V.A.C. Energy-saving type ballasts should not be used in ambient temperatures below manufacturer's recommendations.
- F. Ballasts shall be serviceable while the fixture is in its normally installed position, and shall not be mounted to removable reflectors or wireway covers unless so specified.

2.3 LAMPS

A. Fluorescent Lamps:

1. Rapid start fluorescent lamps shall comply with ANSI C78.1; preheat-start type shall comply with ANSI C78.2; and instant-start and cold-cathode lamps shall comply with ANSI C78.3.
2. Chromacity of fluorescent lamps shall comply with ANSI C78.376.
3. The lamps shall include the F32T8, F32T8/U 32 watt energy saving type and EPACT approved F40T12 type if specifically required by contract drawings for special applications.
4. Except as indicated below, lamps shall be energy saving type, have a color temperature between 3500 and 4100°K, a Color Rendering Index (CRI) of not less than 75, and an initial lumen output not less than 2800. "U" tube lamps shall have the same color temperature and CRI limits as the above.
 - a. In utility areas (Electrical, Communication and Mechanical) Service rooms and closets), maintenance closets and non-medical storage spaces, utilize energy saving light-white lamps.
 - b. In areas with ambient temperatures below 60 degrees use the 40 watt version of the lamp above.
 - c. Over the beds in Intensive Care, Coronary Care, Recovery, Life Support, and Observation and Treatment areas; Electromyographic, Autopsy (Necropsy), Surgery, and certain dental rooms (Examination, Oral Hygiene, Oral Surgery, Recovery, Labs, Treatment, and X-Ray) use color corrected lamps having a CRI of 90 or above and a correlated color temperature between 5000 and 6000°K.
 - d. Other areas as indicated on the drawings.

PART 3 - EXECUTION

3.1 INSTALLATION

- A. Installation shall be in accordance with the NEC, manufacturer's instructions and as shown on the drawings or specified.
- B. Align, mount and level the lighting fixtures uniformly.
- C. Avoid interference with and provide clearance for equipment. Where the indicated locations for the lighting fixtures conflict with the locations for equipment, change the locations for the lighting fixtures by the minimum distances necessary as approved by the Resident Engineer.
- D. For suspended lighting fixtures, the mounting heights shall provide the clearances between the bottoms of the fixtures and the finished floors as shown on the drawings.

SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4

- E. Fluorescent bed light fixtures shall be attached to the studs in the walls. Attachment to gypsum board only is not acceptable.
- F. Lighting Fixture Supports:
1. Shall provide support for all of the fixtures. Supports may be anchored to channels of the ceiling construction, to the structural slab or to structural members within a partition, or above a suspended ceiling.
 2. Shall maintain the fixture positions after cleaning and relamping.
 3. Shall support the lighting fixtures without causing the ceiling or partition to deflect.
 4. Hardware for recessed fluorescent fixtures:
 - a. Where the suspended ceiling system is supported at the four corners of the fixture opening, hardware devices shall clamp the fixture to the ceiling system structural members, or plaster frame at not less than four points in such a manner as to resist spreading of the support members and safely lock the fixture into the ceiling system.
 - b. Where the suspended ceiling system is not supported at the four corners of the fixture opening, hardware devices shall independently support the fixture from the building structure at four points.
 5. Hardware for surface mounting fluorescent fixtures to suspended ceilings:
 - a. In addition to being secured to any required outlet box, fixtures shall be bolted to a grid ceiling system at four points spaced near the corners of each fixture. The bolts shall be not less than 6 mm (1/4 inch) secured to channel members attached to and spanning the tops of the ceiling structural grid members. Non-turning studs may be attached to the ceiling structural grid members or spanning channels by special clips designed for the purpose, provided they lock into place and require simple tools for removal.
 - b. In addition to being secured to any required outlet box, fixtures shall be bolted to a plaster ceiling at four points spaced near the corners of each fixture. Pre-positioned 6 mm (1/4 inch) studs or threaded plaster inserts secured to ceiling structural members shall be used to bolt the fixtures to the ceiling. In lieu of the above, 6 mm (1/4 inch) toggle bolts may be used on new or existing

SAMUEL S. STRATTON MEDICAL CENTER ALBANY, NY
EMERGENCY ELECTRICAL UPGRADES
VA NO. 528A8-11-813 PHASE 4

ceiling provided the plaster and lath can safely support the fixtures without sagging or cracking.

- G. Furnish and install the specified lamps for all lighting fixtures installed and all existing lighting fixtures reinstalled under this project.
- H. Coordinate between the electrical and ceiling trades to ascertain that approved lighting fixtures are furnished in the proper sizes and installed with the proper devices (hangers, clips, trim frames, flanges), to match the ceiling system being installed.
- I. Bond lighting fixtures and metal accessories to the grounding system as specified in Section 26 05 26, GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS.
- J. At completion of project, relamp all fixtures which have failed/burned-out lamps. Clean all fixtures, lenses, diffusers and louvers that have accumulated dust/dirt during construction.

- - - E N D - - -