

ATTACHMENT 4

Protective Device Setting Adjustments

Table 2 - Consolidated New Protective Device Settings

Panel	Component	Setting Type	Range	Existing	Corrected
A SWBD	PNL RPA,1, RPB & MPA FDR	LTD	1-4	4	1
A SWBD	ACC-2 FDR	INST	1.5-10	8	6
ATS 1B LOAD	T-ATS 1B B1 FDR	INST	2.5-8	2.5	8
ATS 1B LOAD	T-ATS 1B B1 FDR	STD	0.1-0.5	0.1	0.5
BRF SWBD	MORGUE EM FDR	INST	1-7	7	1
BRF SWBD	BOILER E FDR	INST	3-10	3	8
B SWBD	N2P FDR	INST	1.5-10	10	6
B SWBD	N2X FDR	LTD	1-4	4	3
CHALLENGER SWBD	CHALLENGER MAIN	STPU	2-8	8	4
CHALLENGER SWBD	CHALLENGER MAIN	STD	1-0.3	0.3	0.2
CHALLENGER SWBD	KR & ACCU-1 FDR	STPU	2-8	6	2

WBVAMC
Overcurrent Protective Device Coordination
and Arc Flash Hazard Assessment Report

Panel	Component	Setting Type	Range	Existing	Corrected
CHALLENGER SWBD	KR & ACCU-1 FDR	STD	I-300	300	I
CHALLENGER SWBD	SAC 23 FDR	STD	I-300	300	I
CHALLENGER SWBD	RM C2-14 PNL FDR	STD	I-300	300	I
CHALLENGER SWBD	2nd FLR AC FDR	STD	I-300	300	I
CHALLENGER SWBD	EBP2 FDR	STD	I-300	300	I
E SWBD	E1 FDR	INTS	3-8	8	4
EBPD	GEN 2 MAIN	INTS	1.5-12	1.5	12
EBPD	EBPD MAIN	INTS	1.5-9	1.5	4
EBPD	LOAD BANK TEST FDR	INTS	1-6	6	1
EBPD	T-ATS 7 B1 FDR	INTS	1-7	7	1
EC4-3	EC4-3 FDR	INTS	1-7	5	7
EDP SWBD	GEN 3 MAIN	INTS	1.5-15	3	4
EDP SWBD	GEN 3 MAIN	STPU	1.5-9	3	4
EDP SWBD	ATS 2 E FDR	INTS	1-10	1	5
EDP	EDP MAIN	INTS	1-6	6	1
EDP	ELEV 1,2,4 FDR	INTS	1-6	6	4
EDP	ELEV 3 FDR	INTS	1-6	6	4
EDP	ATS 7-B1 N FDR	INST	2.5-10	10	4
EDP	ATS 7-B1 N FDR	LTD	1-4	2	4
EDP	T-ATS 7 B1 FDR	INST	1-6	1	6
EDP	T-ATS 7 B1 FDR	STPU	1-7	1	7
EECR RISER	ATS 7 E FDR	INTS	1-7	1	7
EECR RISER	ATS N E FDR	INTS	2-10	8	10
EECR RISER	ATS N E FDR	STD	1-5	0.1	0.5
EELS RISER	ATS 8 E FDR	INTS	1-10	1	9
EMDP-1 SWBD	GEN 1 MAIN	INST	2-15	2	6
EMDP-1 SWBD	GEN 1 MAIN	STPU	1.5-10	1.5	6
EMDP-1 SWBD	EMDP-1 MAIN	INST	1.5-15	6	4.5
EMDP-1 SWBD	EMDP-1 MAIN	STPU	1.5-9	6	4.5
GE SWBD	GE MAIN	LTD	1-4	3	2
GE SWBD	CHALLENGER GE TIE	STPU	2-8	4	5
GE SWBD	CHALLENGER GE TIE	STD	I-0.3	0.3	I

WBVAMC
Overcurrent Protective Device Coordination
and Arc Flash Hazard Assessment Report

Panel	Component	Setting Type	Range	Existing	Corrected
LPA	PNL LP, LPA&B FDR	LTD	1-4	3	1
MCC 5	MCC 5 FDR	INST	2.5-10	8	10
MCC CH1	MCC CH1 FDR	STPU	2-10	4	10
MCC CH1	MCC CH1 MAIN	INST	2.5-8	8	4
MCC CH1	MCC CH1 MAIN	LTD	2-24	7	2
MDS SWBD	MDS MAIN	LTD	4-36	20	4
NELS RISER	ATS 4 E FDR	INST	5-10	5	10
NLP RISER	N LTG BUS FDR	INST	2.5-10	5	7
P1D	L1D,1 P1D FDR	LTD	1-4	4	2
PNL NMP	NMP FDR	LTD	1-4	4	2
PNL SP	SP FDR	LTD	1-4	4	2
SPP RISER	S POWER BUS FDR	LTD	2-14	6	3
SECR RISER	ATS 1 E FDR	INST	1-10	1	9
SELS RISER	ATS 3 E FDR	INST	1-7	1	7
ULP	ULP FDR	INST	1-7	1	7
X-RAY EO 4TH					
FLR GE					
X-RAY EO 4TH					
FLR GE					
X-RAY EO 4TH					
FLR GE					