



NOTES:

- 1 DOOR FRAME SHALL BE PRE-DRILLED FOR DOOR CONTACTS AND DOOR ELECTRIFIED HARDWARE. COORDINATE INSTALLATION WITH DOOR HARDWARE PROVIDER.
- 2 ELECTRICAL CONTRACTOR TO PROVIDE CONTINUOUS CONDUIT PATHWAYS, SECURITY CABLING (3-PAIR #18AWG, EPS, STRANDED, COPPER) AND SECURITY COMPONENTS COMPATIBLE WITH EXISTING HSPD-12 GRADE PHYSICAL ACCESS CONTROL SYSTEM (PACS). COORDINATE WITH MR. THOMAS MAHONEY AT TYCO INTEGRATED SECURITY (571) 338-4480 FOR EXACT PACS REQUIREMENTS PRIOR TO INSTALLATION OF PACS CABLING AND COMPONENTS.
- 3 COORDINATE DOOR HARDWARE WITH ARCHITECTURAL DOOR SCHEDULE.
- 4 ALL DOOR HARDWARE (LOCKS, HINGES, EXIT DEVICES) TO BE PROVIDED BY DOOR HARDWARE PROVIDER.
- 5 PROVIDE 3/4" C CONTINUOUS HOMERUN TO EXISTING PACS CONTROL PANEL LOCATED WITHIN FLOOR INTERSTITIAL SPACE (ABOVE MECHANICAL/ELECTRICAL SERVICE BAYS 4D-160).
- 6 DETAIL REPRESENTS TYPICAL INSTALLATIONS NOT ALL ROUGH-INS ARE REQUIRED. SEE FLOOR PLANS FOR ADDITIONAL INFORMATION.
- 7 PROVIDE SINGLE GANG BACKBOX MOUNTED 42" AFF TO CENTER OF BACKBOX FOR CARD READER (CR). IN LOCATIONS WHERE A SEPARATE BACKBOX IS REQUIRED FOR A PUSHPLATE (PP), OBTAIN REQUIRED SIZE OF BACKBOX AND MOUNTING HEIGHT FROM PUSHPLATE MANUFACTURER.

TYPICAL ACCESS CONTROL DOOR CONFIGURATION

NO SCALE