

**SECTION 26 43 13**  
**SURGE PROTECTIVE DEVICES**

**PART 1 - GENERAL**

**1.1 DESCRIPTION**

- A. This section specifies the furnishing, installation, and connection of Type 2 Surge Protective Devices, as defined in NFPA 70, and indicated as SPD in this section.

**1.2 RELATED WORK**

- A. Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS: Requirements that apply to all sections of Division 26.
- B. Deleted
- C. Deleted
- D. Section 26 24 16, PANELBOARDS: For factory-installed or external SPD.
- E. Deleted

**1.3 QUALITY ASSURANCE**

- A. Quality Assurance shall be in accordance with Paragraph, QUALIFICATIONS (PRODUCTS AND SERVICES) in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS.

**1.4 SUBMITTALS**

- A. Submit in accordance with Paragraph, SUBMITTALS in Section 26 05 11, REQUIREMENTS FOR ELECTRICAL INSTALLATIONS, and the following requirements:
  - 1. Shop Drawings:
    - a. Submit sufficient information to demonstrate compliance with drawings and specifications.
    - b. Include electrical ratings and device nameplate data.
  - 2. Manuals:
    - a. Submit, simultaneously with the shop drawings, companion copies of complete maintenance and operating manuals including technical data sheets, wiring diagrams, and information for ordering replacement parts.
    - b. If changes have been made to the maintenance and operating manuals originally submitted, submit updated maintenance and operating manuals two weeks prior to the final inspection.
  - 3. Certifications: Two weeks prior to final inspection, submit the following.
    - a. Certification by the manufacturer that the SPD conforms to the requirements of the drawings and specifications.

- b. Certification by the Contractor that the SPD has been properly installed.

#### 1.5 APPLICABLE PUBLICATIONS

- A. Publications listed below (including amendments, addenda, revisions, supplement and errata) form a part of this specification to the extent referenced. Publications are referenced in the text by the basic designation only.
- B. Institute of Engineering and Electronic Engineers (IEEE):
  - IEEE C62.41.2-02.....Characterization of Surges in Low-Voltage (1000 V and Less) AC Power Circuits
  - IEEE C62.45-08.....Surge Testing for Equipment Connected to Low-Voltage (1000 V and Less) AC Power Circuits
- C. National Fire Protection Association (NFPA):
  - 70-17.....National Electrical Code (NEC)
- D. Underwriters Laboratories, Inc. (UL):
  - UL 1283-15.....Electromagnetic Interference Filters
  - UL 1449-14.....Surge Protective Devices

### PART 2 - PRODUCTS

#### 2.1 SWITCHGEAR/SWITCHBOARD SPD: NOT USED

#### 2.2 PANELBOARD SPD

- A. General Requirements:
  - 1. Comply with UL 1449 and IEEE C62.41.2.
  - 2. Modular design with field-replaceable modules, or non-modular design.
  - 3. Fuses, rated at 200 kA interrupting capacity.
  - 4. Bolted compression lugs for internal wiring.
  - 5. Integral disconnect switch.
  - 6. Redundant suppression circuits.
  - 7. LED indicator lights for power and protection status.
  - 8. Audible alarm, with silencing switch, to indicate when protection has failed.
  - 9. Form-C contacts rated at 5 A and 250-V ac, one normally open and one normally closed, for remote monitoring of protection status.  
Contacts shall reverse on failure of any surge diversion module or on opening of any current-limiting device.
  - 10. Four-digit transient-event counter.
- B. Surge Current per Phase: Minimum 120kA per phase.

## **2.3 ENCLOSURES**

- A. Enclosures: NEMA 1.

## **PART 3 - EXECUTION**

### **3.1 INSTALLATION**

- A. Installation shall be in accordance with the NEC, as shown on the drawings, and manufacturer's instructions.
- B. Factory-installed SPD: Switchgear, switchboard, or panelboard manufacturer shall install SPD at the factory.
- C. Field-installed SPD: Contractor shall install SPD with conductors or buses between SPD and points of attachment as short and straight as possible. Do not exceed manufacturer's recommended lead length. Do not bond neutral and ground.
  - 1. Provide a circuit breaker as a dedicated disconnecting means for TVSS as shown on drawings.
- D. Do not perform insulation resistance tests on switchgear, switchboards, panelboards, or feeders with the SPD connected. Disconnect SPD before conducting insulation resistance tests, and reconnect SPD immediately after insulation resistance tests are complete.

### **3.2 ACCEPTANCE CHECKS AND TESTS**

- A. Perform in accordance with the manufacturer's recommendations. In addition, include the following:
  - 1. Visual Inspection and Tests:
    - a. Compare equipment nameplate data with specifications and approved shop drawings.
    - b. Inspect physical, electrical, and mechanical condition.
    - c. Verify that disconnecting means and feeder size and maximum length to SPD corresponds to approved shop drawings.
    - d. Verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method.
    - e. Vacuum-clean enclosure interior. Clean enclosure exterior.
    - f. Verify the correct operation of all sensing devices, alarms, and indicating devices.

### **3.3 FOLLOW-UP VERIFICATION**

- A. After completion of acceptance checks and tests, the Contractor shall show by demonstration in service that SPD are in good operating condition and properly performing the intended function.

#### 3.4 INSTRUCTION

- A. Provide the services of a factory-trained technician for one 2-hour training period for instructing personnel in the maintenance and operation of the SPD, on the date requested by the COR.

`---END---